



# 俊英科技（上海）有限公司

中国上海市宜山路900号科技大楼C区1001室 邮编:200233

电话: (021) 64958888

传真: (021) 54235889

## 带通滤波器

型号	中心频率 (MHz)	通带 (MHz)	插入损耗 (dB)	驻波比 (: 1)	抑制频带 (MHz)	尺寸 (mm <sup>3</sup> )
					衰减 > 20dB	长 x 宽 x 高
<b>WGLB-00140</b>	140	110-170	≤4	≤1.5	≥40dB @DC-80&220-2000	7.0x5.0x2.0
<b>WGLB-00960</b>	960	710-1210	≤3.5	≤1.8	≥30dB @DC-460&1260-3000	4.8x4.2x1.5
<b>WGLB-01000</b>	1000	880-1120	≤3.5	≤1.8	≥30dB @10-730&1300-3500	4.8x4.2x1.5
<b>WGLB-01690</b>	1690	1570-1810	≤5	≤2	DC-1200 & 2170-4400	3.2x1.6x1.0
<b>WGLB-01855</b>	1855	1790-1920	≤3.0	≤2.5	DC-1400 & 3700-5500	3.2x1.6x1.0
<b>WGLB-01945</b>	1945	1850-2040	≤3.0	≤2.5	DC-1500 & 3600-5700	3.2x1.6x1.0
<b>WGLB-02593</b>	2593	2496-2690	≤2.5	≤2.0	500-2000	2.0x1.25x0.62
<b>WGLB-02700</b>	2700	2600-2800	≤5.0	≤2.5	DC-1400 DC-1500 4150-4200 4200-5600	3.2x1.6x1.0
<b>WGLB-03600</b>	3600	3400-3800	≤1.5	≤2.0	500-2170 2300-2700 4800-4900 5150-10800	2.0x1.25x0.65

Ver.20190816