



俊英科技（上海）有限公司

上海市徐汇区宜山路900号科技产业化大楼C座1001室 邮编:200233
电话: (021) 64958888 传真: (021) 54235889

带通滤波器

型号	中心频率 (MHz)	通带 (MHz)	插入损耗 (dB)	驻波比 (: 1)	抑制频带(MHz)	尺寸(mm ₃)
					衰减 > 20dB	长x宽x高
WGLB-00120	120	100-140	≤2.5	≤1.5	DC-50&250-700	4.5x3.2x1.5
WGLB-00140	140	110-170	≤4	≤1.5	≥40dB @DC-80&220-2000	5.0x7.0x2.0
WGLB-00960	960	710-1210	≤3.5	≤1.8	≥30dB @DC-460&1260-3000	4.8x4.2x1.5
WGLB-01000	1000	880-1120	≤3.5	≤1.8	≥30dB @10-730&1300-3500	4.8x4.2x1.5
WGLB-01690	1690	1570-1810	≤5.0	≤2.0	DC-1200&2170-4400	3.2x1.6x1.0
WGLB-01855	1855	1790-1920	≤3.0	≤2.5	DC-1400&3700-5500	3.2x1.6x1.0
WGLB-01945	1945	1850-2040	≤3.0	≤2.5	DC-1500&3600-5700	3.2x1.6x1.0
WGLB-02593- 2012	2593	2496-2690	≤3.5	≤3.0	≥16dB 500-2000	2.0x1.2x0.65
WGLB-02700	2700	2600-2800	≤5.0	≤2.5	≥30dB @DC-1500&4150-4200	3.2x1.6x1.0
WGLB-03600- 2012	3600	3400-3800	≤1.5	≤2.0	≥30dB @500-2170&5150-10800	2.0x1.2x0.65

2020.09.25