



# 俊英科技（上海）有限公司

上海市徐汇区宜山路900号科技产业化大楼C座1001室 邮编:200233  
电话: (021) 64958888 传真: (021) 54235889

## 低通滤波器

型号	截止频率@ 3dB (MHz)	通带 (MHz)	插入损耗 (dB)	驻波比 (: 1)	抑制频带(MHz)		尺寸(mm <sub>3</sub> ) 长x宽x高
					衰减 > 20dB	衰减 > 30dB	
WGLL-00080	145	DC~80	≤1.2	≤1.5	200-4500	225-1550	3.2x1.6x1.0
WGLL-00180	270	DC~180	≤1.0	≤1.5	370-6400	525-2350	3.2x1.6x1.0
WGLL-00190	280	DC~190	≤1.0	≤1.5	400-6550	510-2850	3.2x1.6x1.0
WGLL-00225	350	DC~225	≤1.0	≤1.5	460-5500	510-2500	3.2x1.6x1.0
WGLL-00320	460	DC~320	≤1.0	≤1.5	560-5300	640-2500	3.2x1.6x1.0
WGLL-00400	525	DC~400	≤1.2	≤1.5	660-5500	680-3000	3.2x1.6x1.0
WGLL-00490	640	DC~490	≤1.2	≤1.5	760-4100	800-3400	3.2x1.6x1.0
WGLL-00500-2012	730	DC~500	≤1.0	≤1.5	900-6000	900-1000	2.0x1.2x1.0
WGLL-00530	670	DC~530	≤1.2	≤1.5	800-3400	820-3400	3.2x1.6x1.0
WGLL-00575	770	DC~575	≤1.2	≤1.5	900-3200	1050-3200	3.2x1.6x1.0
WGLL-00630	810	DC~630	≤1.2	≤1.5	970-4000	1000-4000	3.2x1.6x1.0
WGLL-00800	1000	DC~800	≤1.2	≤1.5	1400-4500	1500-4500	3.2x1.6x1.0
WGLL-00900	980	DC~900	≤1.3	≤1.5	1400-6500	1450-5400	3.2x1.6x1.0
WGLL-01000	1342	DC~1000	≤1.0	≤1.5	1550-6000	2000-5500	3.2x1.6x1.0
WGLL-01000-2012	1240	DC~1000	≤1.8	≤1.5	1550-10000	1900-6000	2.0x1.2x1.0
WGLL-01200	1580	DC~1200	≤1.2	≤1.5	1800-6500	2000-6000	3.2x1.6x1.0
WGLL-01325	1605	DC~1325	≤1.0	≤1.5	2100-6000	2200-5500	3.2x1.6x1.0
WGLL-01400	1750	DC~1400	≤1.0	≤1.5	1975-6800	2500-5500	3.2x1.6x1.0
WGLL-01500	1745	DC~1500	≤1.3	≤2.0	1970-6800	2000-6600	3.2x1.6x1.0
WGLL-01700	1750	DC~1700	≤1.0	≤1.5	2500-7000	3000-6500	3.2x1.6x1.0
WGLL-01800	2060	DC~1800	≤1.3	≤2.0	2350-7500	2500-7200	3.2x1.6x1.0
WGLL-01800-2012	1925	DC~1800	≤2.2	≤2.0	2450-8500	2500-6500	2.0x1.2x1.0
WGLL-02000	2275	DC~2000	≤1.3	≤1.5	3000-8000	3100-3500	3.2x1.6x1.0
WGLL-02180-1005	2820	1695~2180	≤1.15	≤2.0	3350-4360	5085-6540	1.0x0.5x0.5
WGLL-02250	2425	DC~2250	≤1.3	≤1.5	2850-7200	3000-6000	3.2x1.6x1.0
WGLL-02400	2800	DC~2400	≤1.5	≤1.5	3600-5000	3700-4000	3.2x1.6x1.0
WGLL-02500	3075	DC~2500	≤1.3	≤1.5	3675-8000	3800-6100	3.2x1.6x1.0
WGLL-02600	3125	DC~2600	≤1.3	≤1.5	3560-8400	3900-8000	3.2x1.6x1.0
WGLL-02750	3230	DC~2750	≤1.2	≤1.5	4000-8400	4100-6800	3.2x1.6x1.0
WGLL-02850	3230	DC~2800	≤1.0	≤1.5	4000-9000	4200-7400	3.2x1.6x1.0
WGLL-02850-2012	3090	DC~2850	≤1.8	≤2.0	3800-12000	3900-9000	2.0x1.2x1.0
WGLL-03000	3520	DC~3000	≤0.9	≤1.5	4200-8000	4200-6000	3.2x1.6x1.0
WGLL-03400	4090	DC~3400	≤1.2	≤1.5	4550-8000	4790-6000	3.2x1.6x1.0

型号	截止频率@ 3dB (MHz)	通带 (MHz)	插入损耗 (dB)	驻波比 (: 1)	抑制频带(MHz)		尺寸(mm <sub>3</sub> ) 长x宽x高
					衰减 > 20dB	衰减 > 30dB	
WGLL-03400-2012	3750	DC~3400	≤2.1	≤2.0	4700-15000	5000-9000	2.0x1.2x1.0
WGLL-03500	4090	DC~3500	≤1.2	≤1.5	4550-8000	4790-6000	3.2x1.6x1.0
WGLL-03600	4090	DC~3600	≤1.2	≤1.5	4550-8000	4790-6000	3.2x1.6x1.0
WGLL-03700	4090	DC~3700	≤1.2	≤1.5	4550-8000	4790-6000	3.2x1.6x1.0
WGLL-03900	5090	DC~3900	≤1.5	≤1.5	6000-13000	6250-8300	3.2x1.6x1.0
WGLL-04400	5290	DC~4400	≤1.0	≤1.5	6700-13000	6280-9800	3.2x1.6x1.0
WGLL-06400	7200	DC~6400	≤1.4	≤2.0	8300-12500	8500-10200	3.2x1.6x1.0
WGLL-06700	7940	DC~6700	≤1.2	≤1.5	9300-16000	9500-11000	3.2x1.6x1.0

2021.09.17