



俊英科技（上海）有限公司

上海市徐汇区宜山路900号科技产业化大楼C座1001室 邮编:200233
电话: (021) 64958888 传真: (021) 54235889

带通滤波器

| 型号 | 中心频率 (MHz) | 通带 (MHz) | 插入损耗 (dB) | 驻波比 (: 1) | 抑制频带(MHz) | 尺寸(mm ₃) |
|-----------------|---------------|-------------|--------------|--------------|-------------------------------|----------------------|
| | | | | | 衰减 > 20dB | 长x宽x高 |
| WGLB-00120 | 120 | 100-140 | ≤2.5 | ≤1.5 | DC-50&250-700 | 4.5x3.2x1.5 |
| WGLB-00140 | 140 | 110-170 | ≤4 | ≤1.5 | ≥40dB @DC-80&220-2000 | 5.0x7.0x2.0 |
| WGLB-00960 | 960 | 710-1210 | ≤3.5 | ≤1.8 | ≥30dB @DC-460&1260-3000 | 4.8x4.2x1.5 |
| WGLB-01000 | 1000 | 880-1120 | ≤3.5 | ≤1.8 | ≥30dB @10-730&1300-3500 | 4.8x4.2x1.5 |
| WGLB-01690 | 1690 | 1570-1810 | ≤5.0 | ≤2.0 | DC-1200&2170-4400 | 3.2x1.6x1.0 |
| WGLB-01810-1005 | 1810 | 1710-1910 | ≤2.0 | ≤2.0 | DC-1000 | 1.0x0.5x0.38 |
| WGLB-01855 | 1855 | 1790-1920 | ≤3.0 | ≤2.5 | DC-1400&3700-5500 | 3.2x1.6x1.0 |
| WGLB-01860 | 1860 | 1580-2200 | ≤3.5 | ≤2.5 | DC-1200&5000 | 3.2x1.6x1.0 |
| WGLB-01945 | 1945 | 1850-2040 | ≤3.0 | ≤2.5 | DC-1500&3600-5700 | 3.2x1.6x1.0 |
| WGLB-02593-2012 | 2593 | 2496-2690 | ≤3.5 | ≤3.0 | ≥16dB 500-2000 | 2.0x1.2x0.65 |
| WGLB-02700 | 2700 | 2600-2800 | ≤5.0 | ≤2.5 | ≥30dB @DC-1500&4150-4200 | 3.2x1.6x1.0 |
| WGLB-03600-2012 | 3600 | 3400-3800 | ≤1.3 | ≤2.0 | ≥30dB @500-1785&5150-10800 | 2.0x1.2x0.65 |
| WGLB-03700 | 3700 | 3000-4600 | ≤3.5 | ≤2.5 | DC-1000&2100 | 3.2x1.6x1.0 |
| WGLB-03750-1608 | 3750 | 3300-4200 | ≤3.0 | ≤2.0 | DC-5850 | 1.6x0.8x0.4 |
| WGLB-04300 | 4300 | 4000-4600 | ≤3.0 | ≤2.0 | DC-3250&5100-7000 | 3.2x1.6x1.0 |

2021.01.05